



PRODUCT OVERVIEW





VTC605 DC/DC VOLTAGE CONVERTER

Step up a 12 VDC battery to between 13.5 and 17.0 or 24.0 and 27.5 DC in 0.5 VDC increments (via 3 position DIP switch), or stabilize a 12 or 24 VDC power system.

Safety features include reverse input protection, low input voltage alarm, low output voltage alarm, over temperature shutdown and alarm, a dry contact alarm relay output and output overvoltage crowbar. If the input voltage exceeds the regulated output voltage, the unit simply passes the voltage through with full LC filtering and a single schottky diode drop (0.5 VDC or less). Optional features include remote panel monitoring with On/Off control.

Applications include temporarily brightening 12 volt headlights or work lights, increasing voltage into an automotive or marine ignition system for hotter spark and/or prevention of failures due to voltage drop during engine start, stabilizing 12V and 24 VDC power systems in marine, automotive or aeronautical environments and more.

Available models

Input

10.5-18

10.5-28

Output

12V

24V

Applications













MDS Power Inc.
© Copyright 2022
Specifications subject to change





TECHNICAL SPECIFICATIONS

INPUT			
Volts Nominal DC	10.5-18	10.5-28	
Input Amps (max)	50		
Input Fuse (AGC)	25 x 2 Amp		
Noise on Input Voltage Alarm		< 50 mV	
Current Limit		50 Amps In	

OUTPUT		
Output Volt Nominal VDC	12	24
Output Volts Actual DC	Input - 1 Volt or 13.5 to 17.0 Volts (set by DIP switch), whichever is greater	Input - 1 Volt or 24.0 - 27.5 Volts (set by DIP switch), whichever is greater
Output Current (Amps)	*45	5

^{*} The actual output current capability depends upon the input/output voltage ratio. To obtain the actual output current capability at any given input voltage, use the following formula:

Output Amps = Input Volts/Output Volts x 45

For example, at 11 VDC in and 13.6 VDC out, the output current = $11/13.6 \times 45 = 36.4 \text{ amps}$

Output Crowbar	Programmed output volts x (1.3 ± 1%)	
Output Ripples & Noise	< 50 mV	
Low Output Voltage Alarm	Program Output Voltage minus 2.5 VDC	
Transient Response	< 1V for 50% Surge	
Regulation (Line & Load)	< +/- 0.5%	
Duty Cycle	Continuous 100% for 24 hrs per day	
Efficiency	>90% @ Maximum Output	

MECHANICAL		
Dimensions	9.1 in / 23.1 cm Long x 7.8 in/ 19.8 cm Wide x 4.3" / 10.9 cm High	
Clearance	1.0" / 2.5cm all around	
Weight	6.0 lb / 2.7 kg	
Material and Finish	Marine Grade Black Anodized Aluminum with 18-8 Stainless Fasteners	
Mounting	Wall or Shelf Mount	
Connections	Input: Flying Leads – Red & Black, 4 ft / 1.25 m length, 2 x 10 AWG Output: Beau 4 position terminal block, 2 positive, 2 negative	

ENVIRONMENTAL AND SAFETY		
Operating Temperature	-25°C to +40°C @ maximum output. Derate Linearly 2.5% per °C from 40°C (Optional -40°C wide temperature range available)	
Humidity	0 - 95% Relative Humidity (non-condensing) with standard conformal coating	
Emissions	Meets FCC Part 15, Class B	
Isolation	Input-Case, Input-Output and Output-Case 1500 VDC	
Audible Noise	None	
Duty Cycle	Continuous	
Warranty	Five Years	
Safety	Designed to meet CSA 22.2.107.1 & UL458	

OPTIONS

- · Paralleling Diodes
- European ROHS Compliant (Lead Free Manufactured)
- Electric Fork Lift (Filtering and Surge Suppression)
- Open Frame (No chassis just heat sink bars)
- Safety Special Inspection (CSA/UL)
- Ruggedized and wide temperature
- Custom input/output available

DIMENSIONS

